100W TRANSFORMER BY TRU-SCAPES

Model No: TS-TBPT-100

The Tru-Scapes 100W Transformer has an output rating of a 100 watts at 12 Volt AC. The load connected to the transformer should not exceed 100 watts. Includes an integrated timer and photocell. Our 100Watt Transformer boasts high quality, reliability, value, and aesthetic visual appeal that will add elegance to your landscape design.

For use on 120 Volt Circuits ONLY. Outdoor receptacles should be of "GFCI" type. Not for use with submersible fixtures.

100W Transformer Specifications

- Input Voltage: 120 Volts
- Frequency (Hz): 60Hz
- Power Rated: 100W
- Terminals: Single-Tap
- Exiting Current with No Load: 210 mA Max
- Exiting Current with Full Load: 1050 mA Max
- Voltage Output: 12.0 Volts ±5% AC
- Current Output: 8.33 Amps
- Output Voltage without Load: 12.5 Volts ±5%
- Cord Length: 6' Plugin cord
- Unit Measurements: 4.25" W x 6.25" H x 3.75"
- Exterior Construction: Heavy-duty plastic construction. Rugged and able to withstand most outdoor weather conditions.
- Timer & Photocell: Includes integrated Timer and Photocell