


TRANSFORMERS

DATA SPECIFICATION SHEET



PRODUCT OVERVIEWS

Tru-Scapes® Transformers

Tru-Scapes offers a range of high-quality low-voltage transformers designed to meet the needs of various outdoor lighting installations. Each transformer is crafted with durable, weather-resistant materials and built for reliable performance, ensuring your landscape lighting operates efficiently. The Tru-Scapes transformer series includes four models: 100W, 200W, 300W, and 400W, each offering different power capacities to suit small to large-scale installations.



Scan to Visit Our Website!

SPECIFICATIONS

- Power Capacities:
 - 100W Model (TS-T100)
 - 200W Model (TS-T200)
 - 300W Model (TS-T300)
 - 400W Model (TS-T400)
- Input voltage: 120V AC (All Models)
- Output voltage: 12V/15V AC (multi-tap, All Models)
- Material: Stainless steel housing (All Models)
- Dimensions (L x W x H):
 - 100W Model: 6.5" x 4.5" x 3.5"
 - 200W Model: 8" x 5.5" x 4.5"
 - 300W Model: 10" x 6.5" x 5.5"
 - 400W Model: 11.5" x 7" x 6"
- Weight:
 - 100W Model: 5.5 lbs
 - 200W Model: 7.2 lbs
 - 300W Model: 9.8 lbs
 - 400W Model: 12.5 lbs
- Cord Length: 6 ft (All Models)
- Mounting: Wall-mountable (All Models)
- Certifications: ETL listed (All Models)
- Protection: Overload and short-circuit protection (All Models)
- Timer/Photocell Compatibility: Yes (All Models)

WARRANTY

- Tru-Scapes Lighting Sockets have a Lifetime Warranty.
- Light fixtures of brass, copper or stainless steel, aluminum, including finishes are warranted for five (5) years.
- LED Bulbs are warranted for five (5) years or 30,000 hours, whichever comes first.
- Stainless Steel, Painted and Weatherproof (plastic housing) transformers, excluding timers and photo cells, are warranted for five (5) years for the original purchaser.
- Tru-Scapes warranties do not cover plants that die or burn because of continuous light shined on them. This is not a defect, but the inherent nature of such plants. Certain acid loving plants such as arborvitae, pine trees, and others must not be exposed to light of any kind for more than 18 hours a day as these plants need time to sleep and allow photosynthesis to naturally occur.
- Low voltage landscape lighting fixture housings made of brass do naturally patina in color which is not a defect. (Please see www.Tru-Scapes.com for cleaning instructions.)
- See our full Warranty details at www.Tru-Scapes.com/faq.

CERTIFICATIONS



Indicates the product meets safety standards tested by Intertek.



Signifies the product has passed safety tests by Underwriters Laboratories.



Ensures the product is dust-tight and highly water-resistant.



CONTACT US

© Copyright 2024,
Tru-Scapes® Registered Trademark •
Bucks County, PA • All Rights Reserved •
contacts@tru-scapes.com
1-800-878-1240

WWW.TRU-SCAPES.COM